



Meinberg Radio Clocks

Lange Wand 9
31812 Bad Pyrmont, Germany
Phone: +49 (5281) 9309-0
Fax: +49 (5281) 9309-30
<https://www.meinbergglobal.com>
info@meinberg.de

GPS Satellite Receiver: Subrack Module with LCD Panel and Control Elements (Eurocard)

The variety of inputs/outputs makes this GPS receiver the first choice for a broad range of applications, including time and frequency synchronization tasks and the measurement of asynchronous time events.

Key Features

- Pulses per second and per minute
- 2 time trigger inputs
- 2 RS-232 interfaces
- Alarm output
- DDS frequency synthesizer
- DCF77-simulation
- Included GPSANTv2 antenna uses downconverter technology to enable long transmission routes of up to 1100 m (1200 yards)
- DC-insulated antenna circuit
- Standard frequency outputs
- Flash-EPROM with bootstrap loader
- Optional up to 4 serial ports 4 programmable switching outputs timecode generator (IRIG-B, AFNOR) 5 MHz Frequency Output
- Including GPS antenna, 20m standard cable and manual on USB key

Description

The frequency locking of the master oscillator to the GPS system enables the module GPS180 to generate fixed and programmable standard frequencies with very high accuracy and stability. Various oscillator options allow to meet different requirements concerning the accuracy of the outputs in the most cost efficient way.

The pulse generator of GPS180 generates pulses per second and per minute. Four programmable outputs are available. The pulses are synchronised to UTC second.

Up to four serial interfaces are available for sending time strings. These ASCII telegrams include information regarding time, date and status of the GPS receiver.

The module provides two inputs for measurement of asynchronous time events. These capture events are shown on the LC-Display and can be read via a serial interface.

The front panel integrates a LC-Display that shows information regarding the GPS receiver in different menus. In combination with four push buttons it is also used to setup all configurable parameters.

Characteristics

| | |
|----------------------------------|---|
| Receiver Type | 12 channel GPS C/A-code receiver |
| Status Indicators | Fail-LED shows that the internal timing has not been synchronized or that a system error occurred Lock-LED shows that the calculation of the position has been achieved after reset |
| Type of Antenna | Included [1] GPSANTv2 antenna with innovative downconverter technology that allows transmission routes of up to 300 m using RG58 cable, 700 m using RG213 cable, and 1100 m using H2010 Ultraflex cable |
| Display | LC Display, 4 x 16 characters |
| Synchronization Time | Max. 1 minute in normal operating conditions Max. 25 minutes (average 12 minutes) upon first initialization or in the absence of saved satellite data |
| Frequency Outputs | 10 MHz, 1 MHz, 100 KHz or (optional) 5MHz, TTL level Synthesizer 1/8 Hz up to 10 MHz (TTL level, sine wave 1.5Veff, open drain) Accuracy: $\pm 1 \cdot 10^{-9}$ (timebase OCXO LQ), GPS-synchronous for more than 20 minutes Different oscillators available, look at [2] oscillator options |
| Pulse Outputs | Pulse per second (PPS) and pulse per minute (PPM). TTL level, pulse width: 200 msec |
| Accuracy of Pulse Outputs | Depends on oscillator option: < ± 50 ns (OCXO SQ, OCXO MQ, OCXO HQ, OCXO DHQ, Rubidium) |
| Interface | Two independent serial RS-232-interfaces, menu configurable |

| | |
|--------------------------------------|--|
| Serial Time String Output | Baud Rates: 300, 600, 1200, 2400, 4800, 9600, 19200 Baud Framing: 7E1, 7E2, 7N2, 7O1, 7O2, 8E1, 8N1, 8N2, 8O1 Time String Formats: [3] Meinberg Standard Time String , SAT, Uni Erlangen (NTP), SPA, Sysplex, RACAL, NMEA0183 (RMC,GGA,ZDA), Meinberg GPS, COMPUTIME, ION, [4] Capture String |
| DCF77 emulation | DCF77-emulation, TTL-level |
| Switch outputs | Optional: Four TTL outputs can configured independently for the following modes: - free programmable cyclic or fixed impulses - timecode - timer mode; three 'ON'- and three 'OFF'-states can be setup per day The switch states can be inverted for all three outputs, the impulse lengths are configurable in 10msec steps in a range from 10msec to 10sec. The impulse output can be configured for all channels together to 'always' or 'ifsync'. |
| Supported Timecode Formats | IRIG B002: 100pps, DCLS signal, no carrier, BCD time-of-year IRIG B122: 100pps, AM sine wave signal, 1 kHz carrier, BCD time-of-year IRIG B003: 100pps, DCLS signal, no carrier, BCD time-of-year, SBS time-of-day IRIG B123: 100pps, AM sine wave signal, 1kHz carrier, BCD time-of-year, SBS time-of-day IRIG B006: 100 pps, DCLS Signal, no carrier, BCD time-of-year, year IRIG B126: 100 pps, AM sine wave signal, 1 kHz carrier frequency, BCD time-of-year, Year IRIG B007: 100 pps, DCLS Signal, no carrier, BCD time-of-year, year, SBS time-of-day IRIG B127: 100 pps, AM sine wave signal, 1 kHz carrier frequency, BCD time-of-year, year, SBS time-of-day IEEE1344: Code according to IEEE1344-1995, 100pps, AM sine-wave signal, 1kHz carrier, BCD time-of-year, SBS time-of-day, IEEE1344 expansion for date, time zone, daylight saving and leap second in Control Functions segment C37.118: Like IEEE1344 - with inverted sign bit for UTC offset AFNOR: Code according to NFS-87500, 100pps, AM sine-wave signal, 1kHz carrier, BCD time-of-year, complete date, SBS time-of-day |
| Time-Trigger inputs | Resolution: 100 nsec, triggered by falling TTL slope Time of trigger event readable via RS232-interface |
| Alarm output | Synchronous state of the module, TTL high level if synchronous |
| Dimensions of the front panel | 21HP/3U (106 mm x 128 mm), with integrated membrane keyboard |
| Electrical Connectors | 96-pin DIN 41612 connector |
| Antenna Connector | BNC connector |
| Backup Battery Type | CR2032 (lithium button cell) In the event of loss of power to the main system, this battery powers the real-time clock and also ensures that GNSS almanac data is properly buffered in RAM. Lifetime of lithium battery: Min. 10 years |

| | |
|-------------------------------|---|
| Cable Type | Coaxial cable RG58 indoor or outdoor usage (BNC-, N-Norm-connector) |
| Operating Voltage | +5 V DC |
| Firmware | Flash-EPROM, bootstrap loader |
| Current Draw | +5V 1.1 A to 1.4 A (depending on oscillator type) |
| Board type | Eurocard |
| Supported Temperature | Operational: 0 - 50 °C (32 - 122 °F) Storage: -20 - 70 °C (-4 - 158 °F) |
| Supported Humidity | Max. 85 % (non-condensing) at 40 °C |
| Warranty | Three-year warranty |
| RoHS Status of Product | This product is fully RoHS-compliant. |
| WEEE Status of Product | This product is handled as a B2B (Business to Business) category product. To ensure that the product is disposed of in a WEEE-compliant fashion, it can be returned to the manufacturer. Any transportation expenses for returning this product (at end-of-life) must be covered by the end user, while Meinberg will bear the costs for the waste disposal itself. |

Manual

The English manual is available as a PDF file: [5][Download \(PDF\)](#)

Links:

[1] <https://www.meinbergglobal.com/english/products/gps-antenna-converter.htm>

[2] <https://www.meinbergglobal.com/english/products/specs/gpsopt.htm>

[3] <https://www.meinbergglobal.com/english/specs/timestr.htm>

[4] <https://www.meinbergglobal.com/english/specs/capstr.htm>

[5] <https://www.meinbergglobal.com/download/docs/manuals/english/gps180.pdf>