



### Meinberg Funkuhren

Lange Wand 9

31812 Bad Pyrmont, Germany Phone: +49 (5281) 9309-0 Fax: +49 (5281) 9309-30 https://www.meinbergglobal.com

info@meinberg.de

## LNE: Additional ethernet ports for LANTIME time servers

LANTIME Network Expansion LNE, additional network ports for LANTIME Time Server

## **Important Note**

This product is no longer available. We will of course continue to provide support for units that have already been purchased and are still in use. Please contact our [1] Sales Team for further details.

This product has been discontinued and has been replaced with: [2]

## **Key Features**

- Lantime Expansion for two additional 10/100MBIT Network Connections
- Status LEDs: Connect, Activity, Speed
- RJ45 Network Connectors in the Front Panel



# **Description**

The module LNE extends a LANTIME NTP time server (3U models) with four additional network connections.

LANTIME models in 1U cases can be ordered with two additional network ports.

The additional ports can be used to provide time synchronization to additional separate networks or - by using a feature called "bonding" - to configure redundant network connections (note: the involved active network components like switches have to support this).

## **Characteristics**

Status Indicators	For each network connection: 'Connect', 'Activity' and 'Speed'
Interface	10/100MBIT via RJ45-Jack
Dimensions of the front panel	4HP/3U (20mm x 128mm)
Electrical Connectors	rear VG edge connector DIN 41612, type C 64, rows a + c RJ45 connectors
Board Type	Eurocard
Board Dimensions	160 mm x 100 mm, 1,5 mm Epoxy
Supported Temperature	Operational: 0 - 50 °C (32 - 122 °F) Storage: -20 - 70 °C (-4 - 158 °F)
Supported Humidity	Max. 85 % (non-condensing) at 40 °C
RoHS Status of Product	This product is fully RoHS-compliant.
WEEE Status of Product	This product is handled as a B2B (Business to Business) category product. To ensure that the product is disposed of in a WEEE-compliant fashion, it can be returned to the manufacturer. Any transportation expenses for returning this product (at end-of-life) must be covered by the end user, while Meinberg will bear the costs for the waste disposal itself.

### Manual

There is no online manual available for this product.: [3] Contact us

#### Links:

- [1] mailto:sales@meinberg.de
- [2] https://www.meinbergglobal.com/english/archive/lne-gbe.htm
- [3] mailto:info@meinberg.de